

Group 63 92000.	Build-in power supplies
Position No	006
Model/type	FSP145-60G.W
Data	7/4A 115/230Vac 60/50Hz
Other specification	Cl. I. DC-outputs: 18A +5V, 4.2A +12V, 12A +3.3V, 0.3A -5V, 0.5A -12V, 0.8A +5Vsb. +5V & +3.3V maximum 90W. Total maximum output power is 145W. The symbol "." may be I, N, T or P and designate different chassis types
Group 63 92000	Build-in power supplies
Position No	007
Model/type	FSP200-60G.W
Data	10/5A 115/230Vac 60/50Hz
Other specification	Cl. I. DC-outputs: 21A +5V, 7A +12V, 14A +3.3V, 0.3A -5V, 0.5A -12V, 0.8A +5Vsb. +5V & +3.3V maximum 105W. Total maximum output power is 200W. The symbol "." may be I, N, T or P and designate different chassis types
Group 63 92000	Build-in power supplies
Position No	008
Model/type	FSP235-60G.W
Data	10/5A 115/230Vac 60/50Hz
Other specification	Cl. I. DC-outputs: 22A +5V, 8A +12V, 14A +3.3V, 0.3A -5V, 0.8A -12V, 0.8A +5Vsb. +5V & +3.3V maximum 124W. Total maximum output power is 235W. The symbol "." may be I, N, or T and designate different chassis types
Group 63 92000	Build-in power supplies
Position No	009
Model/type	FSP250-60G.W
Data	10/5A 115/230Vac 60/50Hz
Other specification	Cl. I. DC-outputs: 25A +5V, 8A +12V, 14A +3.3V, 0.3A -5V, 0.8A -12V, 0.8A +5Vsb. +5V & +3.3V maximum 145W. Total maximum output power is 250W. The symbol "." may be I, N, or T and designate different chassis types
Group 63 92000	Build-in power supplies
Position No	010
Model/type	FSP250-61G.(AMD)
Data	8/4A 115/230Vac 60/50Hz
Other specification	Cl. I. DC-outputs: 25A +5V, 7A +12V, 15A +3.3V, 0.3A -5V, 0.8A -12V, 1.0A +5Vsb. +5V & +3.3V maximum 150W. Total maximum output power is 250W. The symbol "." may be N or T and designate different chassis types